# **OSRAM**

# **DIADEM CHROME**

Only amber during operation



### **Chrome design**

Thanks to cutting edge interference and absorber coating

### Amber when ON

Only amber when operating, otherwise almost invisible

### Homogenous appearance

Reflector has a fully homogenous chrome look





### The design light with chrome look

OSRAM DIADEM CHROME signal lamps have a strikingly exclusive design: their chrome look made possible by a cutting edge interference and absorber coating. The lamps emit amber light only when operational. At other times, they are almost invisible and have no irritating color effects. DIADEM CHROME lamps are ideal for all indicator lights with clear covers.

## Product family datasheet

### Technical data

	Product info	Product information		Electrical data				
Product description	Order	Application (Category	Power	Nominal	Nominal	Test	Luminou	
	reference	and Product specific)	input	voltage	wattage	voltage	s flux	
DIADEM CHROME PY21W	7507DC	Auxiliary lamp	25 W	120 V	2100 W	13.5 V	280 lm	
DIADEM CHROME WY5W 1)	2827DC	Auxiliary lamp	5 W	120 V	500 W	13.5 V	30 lm	

		Dimensions & weight	Lifespan		Capabilities	Certificates & standards
Product description	Luminous flux tolerance	Diameter	Lifespan B3	Lifespan Tc	Technology	ECE category
DIADEM CHROME PY21W	±20 %	2500 mm	100 h	250 h	AUX	PY21W
DIADEM CHROME WY5W 1)	±20 %	1000 mm	200 h	500 h	AUX	WY5W

### Environmental information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)

Product description	Date of Declaration	Primary Article Identifier	Candidate List Substance 1	Declaration No. in SCIP database				
DIADEM CHROME PY21W	05-03-2024	4008321972774   4052899241657   4052899417977   4052899418011   4062172211529   4062172271950   4052899979918   4062172394857	No declarable substances contained	In work				
DIADEM CHROME WY5W <sup>1)</sup>	05-03-2024	4008321972750   4052899067790   4052899417915   4052899417953   4052899417939   4052899979925   4062172394758	No declarable substances contained	In work				

<sup>1)</sup> Amber lamp for clear indicators

### Product family datasheet

### **Application advice**

For more detailed application information and graphics please see product datasheet.

### **Disclaimer**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.











